

# Hardware

## DELL iDrac, Lifecycle Update

**F1 - Setup**

**F12 - BootMenue**

### Lifecycle Controller-Update

~~FTP~~ Server: Adresse: ~~ftp.dell.com~~. Keine Anmeldeinformationen. Ggf. Dateipfad: ~~catalog~~. VERALTET

**HTTP/S**-Server: Adresse: **downloads.dell.com**. Ggf. Dateipfad: **catalog**.

**USB**: muß Fat32 sein.

[Download startfähiger ISO-Dateien zum Aktualisieren für PowerEdge Server](#)

iDrac Standardzugang: root / calvin

- Anmeldung im IE schlägt öfter fehl. Manchmal läuft der IE aber dann besser.
- Link im IE zur vertrauenswürdigen Zone hinzu fügen!

iDRAC neu starten, wenn sie hängt: auf dem Server anmelden, CMD-Fenster öffnen und dort den Befehl: „**racadm racreset**“ absetzen.

- Firefox: Zertifikat "DELL iDrac" löschen! Alle Server haben das gleiche Zertifikat, das blockt FF ab.

- \* You must disable the Enhanced Security Mode in Internet Explorer for the Java-based virtual console and virtual media plug-in to function properly. Else, specify the ActiveX plug-in in the iDRAC6 configuration instead of Java. In addition, you must add the iDRAC6 Web URL to the Intranet security zone only. Also, this zone settings must be Medium-Low or lesser, for the control to function properly.
- \* To successfully launch Virtual Media, make sure that you have installed a 64-bit JRE version on a 64-bit operating system with 64-bit browser or a 32-bit JRE version on a 32-bit operating system with 32-bit browser. iDRAC6 does not support 64-bit ActiveX versions. Also, make sure that for Linux, the compat-libstdc++-33-3.2.3-61 related package is installed for launching Virtual Media. On Windows, the package may be included in the .NET framework package.
- \* When the SSL encryption strength is set to "168-bit or higher" or "256-bit or higher" and a downgrade is performed to firmware version 1.97 or lower, the encryption strength defaults to Auto-negotiate. After this if you upgrade the firmware to version 1.98, the encryption strength is set to the previously set "168-bit or higher" or "256-bit or higher" value.

# Hardware

Gute FAQ: <https://faq.hosteurope.de/?cpid=11831>

Eindeutige ID: #1100

Verfasser: Uwe Kernchen

Letzte Änderung: 2023-11-09 19:15