

Netzwerk

Planet Switche

Default IP: 192.168.0.100
selten auch: 192.168.0.254

Default Gateway: 192.168.0.254
admin / admin

Einige Switche haben einen separaten Management-Port (VLAN 1).
Die Switche booten sehr lange (> 30 sek.).

BIOS + Manual Downloads: <https://www.planet.com.tw/en/support/downloads>

Industrie-Switche (DIN-Rail and Wall Mount Kit)

IGS-10020MT

- Managed Gigabit Switch, IP30 Aluminium Gehäuse
- fanless
- 8-port 10/100/1000T + 2-port 100M/1G/2.5G SFP
- LEDs: Power1, Power2, Fault Alarm, Netzwerk Ring, Ring.Owner
per Port: Link, Speed
- WEB-GUI, SNMP 1-3
- Reset Button: <5 sek.: System Reboot, >5 sek.: Factory Reset
- Removable 6-Pin Terminal Block for Power Input
Pin1/2 = Power1, Pin3/4 = Fault Alarm, Pin 5/6 = Power2
- Redundant Power System, 12 - 48V DC (1.25A) oder 24V AC (0.7A)
Netzteil nicht im Lieferumfang!
- Alarm Relay: 24V DC / 1A
- Bootdauer ca. 35 sek. (alle LEDs an)

IGS-5225-4P2S (PoE)

- L2+ Managed Gigabit Switch, IP40 Aluminium Gehäuse
- fanless
- 4-port 10/100/1000T 802.3at/af PoE+ bis 36W + 2-port 100/1000MB SFP
- 1 x RJ45-to-RS232 serial Management Port (115200, 8, N, 1)
- LEDs: Power1, Power2, Fault Alarm (rot), Netzwerk Ring, Ring.Owner
per TCP-Port: PoE, Link
per SFP-Port: Link / Speed
- WEB-GUI, SNMP 1-3
- Reset Button: <5 sek.: System Reboot, >5 sek.: Factory Reset
- Redundant Power System, Dual 48~56V DC (>51V DC for PoE+ output
recommended), 6 - 152W

Seite 1 / 2

(c) 2024 Uwe Kernchen <news@uwe-kernchen.de> | 2024-05-08 18:54

URL: <https://uwe-kernchen.de/phpmyfaq/index.php?action=faq&cat=4&id=440&artlang=de>
(C) <https://uwe-kernchen.de>

Netzwerk

Netzteil nicht im Lieferumfang!

- PoE mit PoE Usage Monitor, PoE Scheduler
- supported Modbus TCP/IP protocol

19" Switche

GS-4210-8T2S

- Managed Edge Switch with Advanced L2/L4 Switching
- fanless
- 8x 10/100/1000BASE-T RJ45 Auto-MDI/MDI-X ports
- 2x 100/1000BASE-X SFP interfaces (dual mode and DDM)
- 1x RS-232-to-RJ45 serial Management Port (115200, 8, N, 1)
- LEDs: Power, Sys
per Port: Link/Akt
- WEB-GUI, SNMP 1-3
- Reset Button: <5 sek.: System Reboot, >5 sek.: Factory Reset
- Dual Firmware Images

GS-4210-24T4S

- Managed Switch with Advanced L2/L4 Switching
- fanless
- 24x 10/100/1000BASE-T RJ45 Auto-MDI/MDI-X ports
- 4x 100/1000BASE-X SFP interfaces (dual mode and DDM)
- 1x RS-232-to-RJ45 serial Management Port (115200, 8, N, 1)
- LEDs: Power
per TCP-Port: 1000 LNK/ACT (Green), 10/100 LNK/ACT (Orange)
per SFP-Port: 1000 LNK/ACT (Green), 100 LNK/ACT (Orange)
- WEB-GUI, SNMP 1-3
- Reset Button: <5 sek.: System Reboot, >5 sek.: Factory Reset

Eindeutige ID: #1439

Verfasser: Uwe Kernchen

Letzte Änderung: 2023-12-02 19:45